

| Total Modules | Single Face Size | Watts | Amps @120V | Qty 20 Amp Breakers | Amps @208V | Qty 20 Amp Breakers | Amps @240V | Qty 20 Amp Breakers |
|---------------|------------------|-------|------------|---------------------|------------|---------------------|------------|---------------------|
| 4 | 2 x 4 | 203 | 2.6 | 1 | 1.5 | 1 | 1.3 | 1 |
| 6 | 2 x 6 | 304 | 3.9 | 1 | 2.3 | 1 | 2.0 | 1 |
| 8 | 2 x 8 | 406 | 5.2 | 1 | 3.0 | 1 | 2.6 | 1 |
| 9 | 3 x 6 | 456 | 5.9 | 1 | 3.4 | 1 | 2.9 | 1 |
| 10 | 2 x 10 | 507 | 6.5 | 1 | 3.8 | 1 | 3.3 | 1 |
| 12 | 3 x 8 | 608 | 7.8 | 1 | 4.5 | 1 | 3.9 | 1 |
| 12 | 4 x 6 | 608 | 7.8 | 1 | 4.5 | 1 | 3.9 | 1 |
| 15 | 3 x 10 | 761 | 9.8 | 1 | 5.6 | 1 | 4.9 | 1 |
| 15 | 5 x 6 | 761 | 9.8 | 1 | 5.6 | 1 | 4.9 | 1 |
| 16 | 4 x 8 | 811 | 10.4 | 1 | 6.0 | 1 | 5.2 | 1 |
| 18 | 3 x 18 | 913 | 11.7 | 1 | 6.8 | 1 | 5.9 | 1 |
| 18 | 6 x 6 | 913 | 11.7 | 1 | 6.8 | 1 | 5.9 | 1 |
| 20 | 4 x 10 | 1014 | 13.0 | 1 | 7.5 | 1 | 6.5 | 1 |
| 24 | 4 x 12 | 1217 | 15.6 | 1 | 9.0 | 1 | 7.8 | 1 |
| 24 | 6 x 8 | 1217 | 15.6 | 1 | 9.0 | 1 | 7.8 | 1 |
| 25 | 5 x 10 | 1268 | 16.3 | 2 | 9.4 | 1 | 8.1 | 1 |
| 30 | 5 x 12 | 1521 | 19.5 | 2 | 11.3 | 1 | 9.8 | 1 |
| 30 | 6 x 10 | 1521 | 19.5 | 2 | 11.3 | 1 | 9.8 | 1 |
| 35 | 5 x 14 | 1775 | 22.8 | 2 | 13.1 | 1 | 11.4 | 1 |
| 35 | 7 x 10 | 1775 | 22.8 | 2 | 13.1 | 1 | 11.4 | 1 |
| 36 | 6 x 12 | 1825 | 23.4 | 2 | 13.5 | 1 | 11.7 | 1 |
| 40 | 8 x 10 | 2028 | 26.0 | 2 | 15.0 | 1 | 13.0 | 1 |
| 42 | 6 x 14 | 2129 | 27.3 | 2 | 15.8 | 1 | 13.7 | 1 |
| 42 | 7 x 12 | 2129 | 27.3 | 2 | 15.8 | 1 | 13.7 | 1 |

The reference table above is for quick reference. Please consult quotation and separate display schematics for final information. All components are auto switching between 120 and 240 Volts. Maximum Amperage per lead: 16 Amps @120V. Multiple leads can be connected together and share a breaker. Multiple circuits may share the same neutrals. Maximum Display Electrical Requirements Per Face are shown for STAX6.3mm and 9.5mm. Follow your local NEC Codes & regulations.